# C7232A,B Sensor and Controller

CARBON DIOXIDE SENSOR

#### PRODUCT DATA



### **FEATURES**

- Models available with LCD that provides sensor readings and status information.
- Non-Dispersion-Infrared (NDIR) technology used to measure carbon dioxide gas.
- Gold-plated sensor provides long-term calibration stability.
- Device provides voltage output based on CO<sub>2</sub> levels.
- Models available with SPST relay output.
- Used for CO<sub>2</sub> based ventilation control.
- Automatic Background Calibration (ABC) algorithm based on long-term evaluation reduces required typical zero-drift check maintenance.

## **APPLICATION**

The C7232 Sensor and Controller is a stand-alone carbon dioxide ( $\mathrm{CO}_2$ ) sensor for use in determining ventilation necessity with HVAC controllers. The C7232 measures the  $\mathrm{CO}_2$  concentration in the ventilated space or duct. The C7232 is used in ventilation and air conditioning systems to control the amount of fresh outdoor air supplied to maintain acceptable levels of  $\mathrm{CO}_2$  in the space.

#### **Contents**

Application	
Features	
Specifications	2
Ordering Information	2
Installation	3
Wiring	4
Calibration	6
Checkout	6
Appendix	7





### **SPECIFICATIONS**

**Models:** C7232 Sensor and Controller. A stand-alone carbon dioxide (CO<sub>2</sub>) sensor with two jumper-adjustable outputs

(one analog and one spst relay). C7232A: Wall mount model. C7232B: Duct mount model.

NOTE: Models are available with or without a 4-digit LCD

that indicates the current CO<sub>2</sub> concentration.

**Dimensions:** 

C7232A: See Fig. 1. C7232B: See Fig. 2.

**Sensor Performance Ratings:** 

Response Time: 2 min. Carbon Dioxide Sensor:

Operation: Non-dispersive infrared (NDIR).

Sampling: Diffusion.

Range: 0 to 2000 ppm ±5% and ±50 ppm.

Annual Drift: 20 ppm (nominal).

**Electrical Ratings:** 

Power Supply: 24 Vac ±20%, 50/60 Hz (Class 2).

Maximum Power Consumption: 3W. Peak Current (at 20 ms): 600 mA.

Relay:

Configuration: Shipped N.O. (reconfigure with software.)

Contact Rating: 1A at 50 Vac/24 Vdc.
Minimum Permissible Load: 1 mA at 5 Vdc.

Linear Analog Output:

Voltage: 0/2-10 Vdc (resistive load greater than

5000 ohms).

Current: 0/4-20 mA (resistive load less than 500 ohms).

Outputs (Jumper Adjustable, see Table 2):

Analog: 0-10 Vdc (Default: 2-10 Vdc, 500 to 1500 ppm). Relay: Normally Open Spst (Default: Close at 800 ppm).

**Ambient Ratings:** 

Temperature:

Operating: +32°F to +122°F (0°C to +50°C). Storage: -4°F to +158°F (-20°C to +70°C).

Relative Humidity (non-condensing): 0 to 95 percent.

CO<sub>2</sub> Pressure Dependence: 1.4% change in reading per 1 kPa deviation from 100 kPa.

#### **Connections:**

Wiring:

C7232A: 20-gauge cable with six 8 in. leadwires. C7232B: 20-gauge cable with six 6 in. leadwires.

#### Mounting:

C7232A: Vertical surface with standard single-gang junction box.

C7232B: Sheet metal duct with a sampling tube.

#### Automatic Background Calibration (ABC) default: On.

#### Approvals:

CE.

Underwriters Laboratories Inc. Listed, File No. E4436.

C7232B: Flammability Rating, UL94-5V.

C7232A: NEMA1. C7232B: NEMA3.




Fig. 1. C7232A dimensions in in. (mm).




Fig. 2. C7232B dimensions in in. (mm).

# **ORDERING INFORMATION**

When purchasing replacement and modernization products from your TRADELINE® wholesaler or distributor, refer to the TRADELINE® Catalog or price sheets for complete ordering number.

If you have additional questions, need further information, or would like to comment on our products or services, please write or phone:

- 1. Your local Honeywell Automation and Control Products Sales Office (check white pages of your phone directory).
- Honeywell Customer Care 1885 Douglas Drive North

Minneapolis, Minnesota 55422-4386

In Canada—Honeywell Limited/Honeywell Limitée, 35 Dynamic Drive, Scarborough, Ontario M1V 4Z9. International Sales and Service Offices in all principal cities of the world. Manufacturing in Australia, Canada, Finland, France, Germany, Japan, Mexico, Netherlands, Spain, Taiwan, United Kingdom, U.S.A.

2

63-2571—5

### INSTALLATION

### When Installing this Product...

- Read these instructions carefully. Failure to follow them could damage the product or cause a hazardous condition.
- Check the ratings given in the instructions and on the product to make sure the product is suitable for your application.
- Installer must be a trained, experienced service technician.
- After installation is complete, check out product operation as provided in these instructions.

#### **IMPORTANT**

All wiring must agree with applicable codes, ordinances and regulations.



# **!**∖ CAUTION

Health Hazard.

Improper use can create dangerous situations. Use in application for sensing carbon dioxide only. For life-safety applications, this device can function only as a secondary or lesser device.



# ackslash CAUTION

Electrical Shock or Equipment Damage Hazard. Can shock individuals or short equipment circuitry.

Disconnect power supply before installation.



# CAUTION

Equipment Damage Hazard. Electrostatic discharge can short equipment circuitry.

Ensure that you are properly grounded before handling the unit.

# C7232A Cover Removal/Replacement

### C7232A Cover Removal (see Fig. 3)

- 1. Remove button head socket cap screw and set it aside.
- 2. Insert the head of a small screwdriver into the slot at the center and near the top of the cover.
- Gently pull the handle down toward the bottom of the device until a small gap between the subbase and the cover appears.
- **4.** Remove the screwdriver and pull the cover straight down until it meets a stop.
- 5. Pull the cover straight off the subbase.

### C7232A Cover Replacement

- 1. Feed the wires through the opening in the subbase.
- Place the cover, with a small gap at the top, flat on top of the subbase.
- 3. When the cover rests flat on the subbase, slide it straight up until it latches in place.




Fig. 3. C7232A cover removal.

3

### **Location and Mounting**

C7232 Sensors mount directly on the wall, sheet metal duct, or a panel. When planning the installation, allow enough clearance for maintenance and service. Mount the sensor in a well-ventilated area.

NOTES: Do not install the sensor where it can be affected by:

- drafts or dead spots behind doors and in corners.
- air from ducts.

#### **Wall Mounting**

The C7232 Wall Mount models can be mounted using two or four screws:

- 1. Remove C7232 cover.
- Mount the subbase to the wall using washers and two or four screws (not supplied) appropriate for the wall material.

NOTE: When mounting on a junction box, see Fig. 4.

3. Replace the cover.

### **Duct Mounting (see Fig. 5)**

1. Place gasket on aspiration tube.

#### **IMPORTANT**

Ensure largest tab at tube control end is at the top.

2. Insert tube into duct; attach using screws and washers.

#### **IMPORTANT**

Leakage into the duct or the C7232 box cover from the room will skew the sensor readings. Ensure the box cover and duct seal completely.

**3.** Place o-ring on tube end; mount the control to the tube.




Fig. 4. Junction box mounting (C7232A).




Fig. 5. Duct mounting (C7232B).

### **WIRING**

The factory ships the device with the output default settings shown in Tables 2 and 3. Set the jumpers and wire the device (see Table 1 and Fig. 6).



### CAUTION

Electrical Shock or Equipment Damage Hazard. Can shock individuals or short equipment circuitry.

Disconnect power supply before installation.



# **CAUTION**

Equipment Damage Hazard. Electrostatic Discharge Can Short Equipment Circuitry.

Ensure that you are properly grounded before handling the unit.

#### **IMPORTANT**

4

- All low voltage connections to this device must be 24 Vac Class 2.
- 2. All wiring must comply with applicable local codes, ordinances and regulations.

Table 1. C7232 Wiring Connections (see Fig. 6).

Wire Color	Designation	Function
Red	G+	24 Vac Hot
Black	G0	24 Vac Common
Yellow	OUT1	Analog Output Signal
Brown	M	Analog Output Common
Orange	NO	Relay Output Normally Open
Green	СОМ	Relay Output Common

63-2571—5




Fig. 6. Wiring the C7232.

# **Input Signal**

The C7232 Sensors have an adjustable range. These ranges are determined by the SW1 and SW2 jumper settings (see Table 2).

Table 2. CO<sub>2</sub> Range Jumper Settings

SW1	SW2	AN (ppm)	Relay <sup>a</sup> (ppm)
On	On	0 to 1000	1000
On	Off	0 to 2000	1200
Offb	On <sup>b</sup>	500 to 1500	800
Off	Off	500 to 2000	1200

<sup>&</sup>lt;sup>a</sup> When the level reaches this value, the contacts close; when the level drops 100 ppm below this value, the contacts open.

# **Output Signal**

The output signal can be adjusted for 0/2-10Vdc or 0/4-20mA (see Table 3).

#### **Table 3. Output Signal Jumper Settings**

	OUT				
AN	0-100%	20-100%			
Voltage	0-10Vdc	2-10Vdc			
Current	0-20 mA	4-20 mA			

#### NOTES:

- On duct models, remove the screw holding the board in place to view jumper settings on reverse. (See Fig. 7.)
- The CO<sub>2</sub> settings and the output signal settings are independent of each other. 0-100% and 20-100% are simply markings for the OUT jumper settings on the sensor (to differentiate between the two voltage and the two current ranges) and do not refer to or alter the ppm range chosen.




Fig. 7. C7232 default jumper settings.

#### Example

For a  $CO_2$  setting of 0-2000 ppm and a voltage output of 0-10 Vdc, the output would be as shown in Table 4 (arbitrary points along the analog curve).

Table 4. 0-10 Vdc Output Example.

CO <sub>2</sub> Level (ppm)	0	200	400	600	800	1000	1200	1400	1600	1800	2000
Voltage Output (Vdc)	0	1	2	3	4	5	6	7	8	9	10

For a  $CO_2$  setting of 0-2000 ppm and a voltage output of 2-10 Vdc, the output would be as shown in Table 5 (arbitrary points along the analog curve).

Table 5. 2-10 Vdc Output Example.

CO <sub>2</sub> Level (ppm)	0	250	500	750	1000	1250	1500	1750	2000
Voltage Output (Vdc)	2	3	4	5	6	7	8	9	10

5

63-2571—5

<sup>&</sup>lt;sup>b</sup> Setting when shipped from the factory.

# **CALIBRATION**

Typically, calibration is unnecessary. No calibration kits are available. However, if  ${\rm CO}_2$  gas can be purged from the sensor chamber using a general gas purge device, the sensor can be rezeroed:

#### **IMPORTANT**

Any  $CO_2$  present during calibration skews the sensor zero level resulting in incorrect  $CO_2$  level reports.

- Once the sensor stabilizes, use a screwdriver to connect the two MENU soldering pads.
- 2. The display should indicate CAL.
- 3. Execute the zero calibration by connecting the two ENTER soldering pads.
- The display should return to providing the measured CO<sub>2</sub> level.

### **CHECKOUT**

Perform a quick test of the unit with the unit powered:

- 1. Stand close to the unit and breathe air into the sensor.
- Check the CO<sub>2</sub> level registered by the controller to ensure a strong rise.
- 3. When connected to a damper in a ventilation system, the controller typically signals an increase in air flow.

63-2571—5

6

### **APPENDIX**

#### **IMPORTANT**

This page is only for models with date code prior to 0309.

### **Pre 0309 Date Code Jumper Settings**

### **Input Signal**

The C7232 Sensors have an adjustable range. These ranges are determined by the SW2 and OUT1 jumper settings (see Table 6).

NOTE: When choosing analog output, be sure to set the SW1 jumper to the On position.

Table 6. CO<sub>2</sub> Range Jumper Settings for models with date code prior to 0309.

		Jumper SW1		Jumpe	er SW2
Jumper	Setting	Ona	Off	On <sup>a</sup>	Off
OUT1 <sup>b</sup>	AN1	Х	_c	0 to 1000	0 to 2000
	AN2 <sup>a</sup>	Х	_c	500 to 1500	500 to 2000
Relay Swite	ching <sup>b</sup>	Х		800 <sup>d</sup>	1200 <sup>d</sup>
			Χ	1000 <sup>d</sup>	

<sup>&</sup>lt;sup>a</sup> Setting when shipped from the factory.

#### **Output Signal**

The output signal can be adjusted for 0/2-10Vdc or 0/4-20mA (see Table 7).

Table 7. Output Signal Jumper Settings for models with date code prior to 0309.

AN1 and AN2 (set	OUT				
both the same)	0-100%	20-100%			
Voltage	0-10Vdc	2-10Vdc			
Current	0-20 mA	4-20 mA			

#### NOTES:

7

- On duct models with date code prior to 0309, remove the screw holding the board in place to view jumper settings on reverse. (See Fig. 8.)
- The CO<sub>2</sub> settings and the output signal settings are independent of each other. 0-100% and 20-100% are simply markings for the OUT jumper settings on the sensor (to differentiate between the two voltage and the two current ranges) and do not refer to or alter the ppm range chosen.




Fig. 8. C7232 default jumper settings for models with date code prior to 0309.

<sup>&</sup>lt;sup>b</sup> OUT1 jumper setting does not affect the Relay Switching.

<sup>&</sup>lt;sup>c</sup> The analog output will not work properly when SW1 is Off.

d When the level reaches this value, the contacts close; when the level drops 100 ppm below this value, the contacts open.

# Honeywell

**Automation and Control Solutions** 

Honeywell International Inc. 1985 Douglas Drive North Golden Valley, MN 55422 Honeywell Limited-Honeywell Limitée 35 Dynamic Drive Scarborough, Ontario M1V 4Z9 **Honeywell International** Control Products

Honeywell Building 17 Changi Business Park Central 1 Singapore 486073 **Honeywell Europe S.A.** 3 Avenue du Bourget 1140 Brussels Belgium Honeywell Latin American Region 480 Sawgrass Corporate Parkway

Suite 200 Sunrise FL 33325

